



## GE Magnetic Contacts

### 1038 Series

Surface Mount with Wire Leads



<b>Gap Distance</b>	<b>Closed Loop</b>
1"	1038

<b>Color</b>	White, Mahogany Brown
<b>Quantity</b>	10

100% **TESTED**



1038-N




# 1038 Series

## Surface Mount with Wire Leads

### Installation Instructions

1. Clean mounting surfaces with alcohol pad (included).
2. Align and attach mounting plates for the switch and magnet using tape or screws (included). Wire may be routed on either end or through the top of the switch housing cutouts.
3. Strip loop wire and connect the leads to the alarm loop.
4. Place switch and magnet covers over the center of the mounting plates and slide either left or right until the cover snaps in place.



### UL Specifications

Part Number	Loop Type	Electrical Configuration	Gap Distance*
1038	Closed	N.O.	1"

\* Gap Specifications are nominal and may vary  $\pm 20\%$ . Gap Specifications are for switch to make. Break distance is approximately 1.1 to 1.5 times make.

WARNING: Each electrical rating is an individual maximum and cannot be exceeded!

#### \*\* FORM A (1038)

Voltage: 100 V AC/DC max

Current: 0.5 A max

Power: 7.5 W max



GE Interlogix